



Reckeen SMARTKEY technical specifications

SDI

Video output

Video input

SDI номі SDI Video Input HDMI • 4 x 3G - 3G/HD/SD auto switching • 2 x HDMI 2,0 type A connector with • 3G,12G - 4 x 3G SDI and 2 x 12G SDI support for 1080p60 up to 4k 60p Monitor output • 2 x DP output for monitor 2 x HDMI output for monitor I/O port Tally Output • PC/2 • TL - DB9 - 4 channels PC keyboard Reckeen External Keyboard port • USB • RS – DB9 – RS 232 • 2 x USB 3.0 (front panel) • 4 x USB 3.0 (back panel) Reckeen External Audio port • 1 x USB 3.1 (back panel) LAN – Audio Link Fthernet Gigabit Ethernet LAN Reference input - (Genlock) Black Burst or Tri-Sync Audio output - ADB100 Digital Analog embedded stereo on each SDI and 4 x XLR two channels – professional HDMI balanced analogue audio stereo 2 x AES/EBU differential input (-10dBV, or 4dBu) 1 x Jack 6.3mm – stereo Headphone output Video standards SDI HDMI • SDI • HDMI • SMPTE2082-1 • Video standard – HDMI spec 1.4 2160p (60/59.94/50/30/25) Video standard – HDMI spec 2.0 SMPTE-425M

- · 1080p (60/59.94/50/30/25)
- SMPTE-292M
- · 1080p (30/29.97/25)
- · 1080i (60/59.94/50)
- SMPTE-296M
- 720p (60/59.94/50) SMPTE-259M
- PAL, NTSC

NDI

- NDI input:
- 4 input interchangeably as cam 1 to program out cam 4 with supported stream key or Reckeen chroma key
- · 2 input interchangeably as media 1
- and 2

© NDI® is a trademark of NewTek, Inc

Any information, illustrations and technical data are subject to change without prior notification and/or indication in this folder.

NDI output:

For more information please visit our website at: www.reckeen.com Contact us: sales@reckeen.com

CECKE

keer **LEC**

SDI Video Output • HDMI • 8 x SDI - 3G/HD · HDMI 1.4 type A connector with support • 3G,12G - 6x3G/HD and 2x12G - 4k 60p for 1080p60 Audio input - ADB 100 Analog Digital · embedded stereo on each SDI and HDMI 2 x AES/EBU Video formats SDI HDMI · Input - auto switching 2 x SDI 12G 2160p 60/59.94/50/30/29.97/25 • 6 x SDI 3G 1080p 60/59.94/50/30/29.97/25 1080i 60/59.94/50 · 720p 60/59.94/50 PAL. NTSC PAL NTSC Output • 2 x SDI 12G Output 2160p 60/59.94/50/30/29.97/25 HDMI v1 4 6 x SDI 3G 1080p 60/59.94/50/30/29.97/25

• 1080i 60/59.94/50 720p 60/59.94/50 PAL, NTSC

720p 60/59.94/50 Features

- Downstream Key x2
- Media Format
- MPEG2, MPEG4 and H.264 containers:
- (avi, mpg, mpeg, mp4, mxf, mov)
- Audio: WAV, MP3
- Video Capture Format • H.264 (.mp4) MPEG-2 (.mpg)
- 1080p 60/59.94/50/30/29.97/25
- 1080i 60/59.94/50
- 720p 60/59.94/50
- H.264 up to 4k 30p and 60p

Software

- Reckeen SMARTKEY package:
- · 4 chroma SMARTKEY keyers Reckeen Lite
- VSM Lite Editor (also as a standalone upgrade
- version)
- Still Editor

- · 4 x XLR two channels professional balanced analogue audio stereo differential input (-10dBV, or 4dBu) Two types of microphones – dynamic and condenser with + 48V phantom · Input - auto switching 2 x HDMI v2.0 • 2160p 60/59.94/50/30/29.97/25 1080p 60/59.94/50/30/29.97/25
- 1080i 60/59.94/50 720p 60/59.94/50

номі

- 1080p 60/59.94/50/30/29.97/25
- 1080i 60/59.94/50
- 720p 60/59.94/50
- Still Picture x2
- Picture Format
- .png, .jpg, .bmp • Still Text - x2
- · Still Editor included
- Keyer x4 Chroma Key / Luminance Key
- SMARTKEY with 4 SDI outputs
- Streaming Facebool
- YouTube
- NicoNico
- NDI and custom profiles





THEFIH Multi Chroma Keyer

SCREEN LAYER

TLAYER





PERFECT BROADCASTING **SOLUTIONS**

OBJECT LAVER

OBJECT LAVER

STUDIOLAYER

TALENT LAYER



9 0= 8 0

Reckeen SMARTKEY and Reckeen Lite

Perfect broadcasting solution for professionals.

Reckeen SMARTKEY system enables you to produce professional TV programs in real-time. It is a multi-channel mixer that combines 4 video sources with computer graphics and media. Each of these video sources can be preprocessed using 4 built-in chromatic keys with Smartkey function, thus creating a virtual studio or an advanced composition combining computer graphics and video. SMARTKEY technologies can be used:

• As 4 independent Full HD, High Quality Chroma keys with video background, the Keys' outputs can be processed in an external mixer.

• To make quick transitions of Smartkey channels to the main mixer (switcher) on PRV, PGM outputs in Reckeen LITE systems.

• As a PIP composition in LITE SMARTKEY app, that can be created using VSM - Virtual Space Maker Editor.

RECKEEN SMARTKEY Studio is actually 9 in 1!

RECKEEN SMARTKEY is a complete set of tools and functionalities to create, record and broadcast high-quality video content.

These functionalities include:

- Reckeen Lite virtual studio
- 4 Chroma key channels with SMARTKEY function
- Production switcher
- Audio Mixer
- Still Editor captions and graphic boards generator
- VSM Lite Editor virtual and PIP scenery editor
- MS 3D Paint Editor
- Recorder
- Streamer

Reckeen Lite Production

The production module within Reckeen Lite system is a typical production application that provides all necessary tools needed for live program production. This type of realizations require simultaneous operation on multiple video sources. To make this possible, RECKEEN LITE system allows you to receive external signal sources connected to the input card.

To control the players a simple interface is used – Media Tray.

RECKEEN LITE system, depending on its configuration, enables operating on up to four sources (CAM1 – CAM4). CAM sources are streamed live, for example from a camera connected to the input card. Reckeen Lite is also equipped with NDI signal sources. Remaining signal sources are played by virtual TV players. The players support the following sources: MEDIA1, MEDIA2 for videos, STILL1, STILL2 for static graphics, and Text1, Text2 for text boards. Controlling virtual cameras is easy and convenient thanks to the specially designed VKey-100 keyboard with joystick.

PREVIEW MONITOR PREVIEW MONITOR PRODUCTION LIVE PROGRAM **PREVIEW MONITOR** BIG FIR SCREEN MULTIVIEW DVI or HDMI DVI or HDM or Display Pol r Display Po DVI or HDMI or Display Port **SMARTKEY** CAM TALLY_{x4} 🥌 NDI **4 x SDI outputs 4**K HDMI or SDI 120 CAM 2 SDI - SK1 ЧК SDI - SK2 HDMI or SDI 12G SDI -SK3 CAM 3 SDL - SK CAM 4 AUDIO ΜΙΧ AUDIO MIX 111 **Control Panel** VKey-100 XLR Line IN 1 XI R Out or XLR Line IN 2 **VIDEO RECORDER** HDM or SDI Sound System 6.3 mm Jac 🔄 NDI Headphones **Keyboard and mouse** Microphone Streaming

PA

П

SMARTKEY - Mutli Chroma Keyer

SMARTKEY is a new solution integrating chroma key function with media and



graphics.

How does SmartKey work? Input signals from the cameras, from up to 4 chosen video inputs in Reckeen 3DSPRO Studio & Reckeen SMARTKEY, are sent to chroma keying function.

The purpose of chroma

keying is to remove green or blue background, and be able to place a talent in a virtual studio. SMARTKEY function integrates a result from chroma keying with chosen video clip or still graphics. Chosen video clip or graphics is placed as a background layer, instead of green or blue colour.

Additional feature includes automatic movement of background media to intensify visual dynamic of a created scene. On such background, a layer with a talent, generated by a chroma key, can be placed. In that way, we can obtain four new media streams – SMARTKEY channels (SK 1 to 4), which can be placed directly inside our Reckeen virtual studio systems space, or sent to additional SDI outputs.

Still Editor



The Still Editor module allows you to create captions, text boards and news tickers. With an easy-to-use panel, suitable components can be downloaded from external files, or created from scratch – even

during production and live editing.

MS Paint 3D

-01



JE IT

By using Microsoft 3D Paint editor, which is preinstalled with Reckeen 3D studio, you can create 3D objects that later can be placed in a virtual studio scenography.

This application allows you to implement all sorts of ideas - from simple ones, like three-dimensional subtitles, to the most original 3D objects' designs. Anything created using this application

can be easily and intuitively transferred to our virtual studio, even during live production.

